



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XU/I 2-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	AI 4x U/I 2-wire
HW functional status	From FS02
Firmware version	
• FW update possible	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
• I&M data	Yes; I&M0 to I&M3
• Isochronous mode	No
• Measuring range scalable	No
Engineering with	
• STEP 7 TIA Portal configurable/integrated from version	V14 / -
• STEP 7 configurable/integrated from version	V5.6 and higher
• PCS 7 configurable/integrated from version	V8.1 SP1
• PROFIBUS from GSD version/GSD revision	One GSD file each, Revision 3 and 5 and higher
• PROFINET from GSD version/GSD revision	GSDML V2.3
Operating mode	
• Oversampling	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
• Short-circuit protection	Yes
• Output current, max.	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	
• Address space per module, max.	8 byte; + 1 byte for QI information

Hardware configuration	
Automatic encoding	Yes
<ul style="list-style-type: none"> • Mechanical coding element 	Yes
<ul style="list-style-type: none"> • Type of mechanical coding element 	Type A
Selection of BaseUnit for connection variants	
<ul style="list-style-type: none"> • 2-wire connection 	BU type A0, A1
Analog inputs	
Number of analog inputs	4; Differential inputs
permissible input voltage for voltage input (destruction limit), max.	30 V
permissible input current for current input (destruction limit), max.	50 mA
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), voltages	
<ul style="list-style-type: none"> • 0 to +10 V <ul style="list-style-type: none"> — Input resistance (0 to 10 V) 	Yes; 15 bit 120 k Ω
<ul style="list-style-type: none"> • 1 V to 5 V <ul style="list-style-type: none"> — Input resistance (1 V to 5 V) 	Yes; 15 bit 120 k Ω
<ul style="list-style-type: none"> • -10 V to +10 V <ul style="list-style-type: none"> — Input resistance (-10 V to +10 V) 	Yes; 16 bit incl. sign 120 k Ω
<ul style="list-style-type: none"> • -5 V to +5 V <ul style="list-style-type: none"> — Input resistance (-5 V to +5 V) 	Yes; 16 bit incl. sign 120 k Ω
Input ranges (rated values), currents	
<ul style="list-style-type: none"> • 0 to 20 mA <ul style="list-style-type: none"> — Input resistance (0 to 20 mA) 	Yes; 15 bit 100 Ω ; + approx. 0.7 V diode forward voltage
<ul style="list-style-type: none"> • 4 mA to 20 mA <ul style="list-style-type: none"> — Input resistance (4 mA to 20 mA) 	Yes; 15 bit 100 Ω ; + approx. 0.7 V diode forward voltage
Cable length	
<ul style="list-style-type: none"> • shielded, max. 	1 000 m; 200 m for voltage measurement
Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	
<ul style="list-style-type: none"> • Resolution with overrange (bit including sign), max. 	16 bit
<ul style="list-style-type: none"> • Integration time, parameterizable 	Yes
<ul style="list-style-type: none"> • Interference voltage suppression for interference frequency f_1 in Hz 	16.6 / 50 / 60 Hz
<ul style="list-style-type: none"> • Conversion time (per channel) 	180 / 60 / 50 ms
Smoothing of measured values	
<ul style="list-style-type: none"> • Number of smoothing levels 	4; None; 4/8/16 times
<ul style="list-style-type: none"> • parameterizable 	Yes
Encoder	
Connection of signal encoders	
<ul style="list-style-type: none"> • for voltage measurement 	Yes
<ul style="list-style-type: none"> • for current measurement as 2-wire transducer <ul style="list-style-type: none"> — Burden of 2-wire transmitter, max. 	Yes 650 Ω
<ul style="list-style-type: none"> • for current measurement as 4-wire transducer 	No
Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.01 %
Temperature error (relative to input range), (+/-)	0.005 %/K
Crosstalk between the inputs, min.	50 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.05 %
Operational error limit in overall temperature range	
<ul style="list-style-type: none"> • Voltage, relative to input range, (+/-) 	0.5 %
<ul style="list-style-type: none"> • Current, relative to input range, (+/-) 	0.5 %
Basic error limit (operational limit at 25 °C)	
<ul style="list-style-type: none"> • Voltage, relative to input range, (+/-) 	0.3 %
<ul style="list-style-type: none"> • Current, relative to input range, (+/-) 	0.3 %
Interference voltage suppression for $f = n \times (f_1 \pm 1 \%)$, $f_1 =$ interference frequency	
<ul style="list-style-type: none"> • Series mode interference (peak value of interference < rated value of input range), min. 	70 dB

<ul style="list-style-type: none"> • Common mode voltage, max. 	10 V
<ul style="list-style-type: none"> • Common mode interference, min. 	90 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
<ul style="list-style-type: none"> • Diagnostic alarm 	Yes
<ul style="list-style-type: none"> • Limit value alarm 	No
Diagnoses	
<ul style="list-style-type: none"> • Monitoring the supply voltage 	Yes
<ul style="list-style-type: none"> • Wire-break 	Yes; at 4 to 20 mA
<ul style="list-style-type: none"> • Short-circuit 	Yes; with 1 to 5 V or 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
<ul style="list-style-type: none"> • Group error 	Yes
<ul style="list-style-type: none"> • Overflow/underflow 	Yes
Diagnostics indication LED	
<ul style="list-style-type: none"> • Monitoring of the supply voltage (PWR-LED) 	Yes; green LED
<ul style="list-style-type: none"> • Channel status display 	Yes; green LED
<ul style="list-style-type: none"> • for channel diagnostics 	No
<ul style="list-style-type: none"> • for module diagnostics 	Yes; green/red LED
Potential separation	
Potential separation channels	
<ul style="list-style-type: none"> • between the channels 	Yes; channel group-specific between 2-wire current input group and voltage input group
<ul style="list-style-type: none"> • between the channels and backplane bus 	Yes
<ul style="list-style-type: none"> • between the channels and the power supply of the electronics 	Yes; only for voltage inputs
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes
Ambient conditions	
Ambient temperature during operation	
<ul style="list-style-type: none"> • horizontal installation, min. 	-30 °C; < 0 °C as of FS02
<ul style="list-style-type: none"> • horizontal installation, max. 	60 °C
<ul style="list-style-type: none"> • vertical installation, min. 	-30 °C; < 0 °C as of FS02
<ul style="list-style-type: none"> • vertical installation, max. 	50 °C
Altitude during operation relating to sea level	
<ul style="list-style-type: none"> • Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	31 g

last modified: 4/25/2024 